

# GVLG 48-80 48V80AH

# LITHIUM IRON PHOSPHATE BATTERY

ELECTRICAL SPECIFICATION	
Nominal Voltage	51.2V
Nominal Capacity	80AH
Capacity @16A	5HR
Energy	4096WH
Resistance	≤ <sub>20m</sub> Ω
Efficiency	99%
Self Discharge	< 3% per month



## **MECHANICAL SPECIFICATIONS**

Dimensions (L*W*H)	400*375*258mm
Weight	35 KG
Terminal Type	M8 Screw
Case Material	Metal case
Enclosure Protection	IP66
Cell Type	Prismatic

## **TEMPERATURE SPECIFICATION**

Discharge Temperature	-20 °C to 60 °C
Charge Temperature	0 °C to 55 °C
Storage Temperature	-20 °C to 40 °C
BMS High Temperature	80 °C
Reconnect Temperature	50 °C
Communication	CAN/Bluetooth

### **FEATURE & BENEFITS**

• High Cycle Life : >2000 times @80%DOD for Effectively lower cost of ownership

180A

200A

40V

20A

70A

58.4V

• Built-in BMS Protection: Battery Management System are incorporated to protect battery from OVER CHARGING,

OVER DISCHARING , SHORT CIRCUIT

LIGHT WEIGHT: Dry power lithium batteries has higher energy density, wh/kg is the 3times than SLA battery.

• WIDE OPERATING TEMPERATURE RANGE: Suitable for users in a wider range of application where ambient temperature is unusually high: up to +60° C

STEADY OUTPUT VOLTAGE, VIBRATION & SHOCK RESISTANT, NO MEMORY EFFECT, PRESSURE RESISTANT CELLS

DISTRIBUTED BY GLOBAL MESH COMMUNICATION CO., LTD.

8/1 . ALLEY RAMINTRA 14 INTERSECTION 20 . TARANG . BANGKHEN . BANGKOK 10230 THAILAND. TEL: +66 2509-9988 FAX: +66 2509-8844

Max. Charge Current Charge Voltage

**CHARGE SPECIFICATION** 

**Recommended Charge Current** 

**DISCHARGE SPECIFICATIONS** 

Max. Cont. Discharge

Peak Discharge Current

Discharge Cut-off Voltage



#### SUITABLE APPLICATIONS

- · Lithium Iron Phosphate can be used in any application that would normally use Lead Acid, GEL, or AGM type batteries.
- LiFeP04 in 4S=12.8V and 8S=25.6V is closed to Lead Acid equivalents of the Lithium rechargeable types
- · Suitable applications included caravan, marine, golf carts, solar storage, remote monitoring, switching applications

#### CAUTIONS

- Do NOT expose the battery to water
- · Do NOT expose the battery to fire & high temperature
- Do NOT short circuit, crush, or disassemble
- Only use LiFeP04 charger
- Store at 50% capacity, recharge every 3 months. The storage area should be clean, cool, dry and ventilated.